

Summary	Parameters for changing 1.5HP motor to a 2HP motor on 460V doors				
Products Affected	All 460v System 3 Doors				
Key Word Tags	System3. Motor, Retro, 1.5, 2.0				
Tools/Equipment (If Required)					
Parts/Materials (If Required)					
Related Media					
Author	Aaron Pierringer, RevA M. Burzlaff	Issue Date	4/13/2011	Status	Active

Please Read The Entire Bulletin Before Proceeding

1. After installing the new motor please make sure that the motor is wired for Low Voltage and leave it that way
2. Go into parameters and set P.999 to a 10.
3. Go to parameter P.001 and lock in the value on the right side
4. Call Rytec Customer Service at the number provided below and give them the cycle count you got from P.001
5. We will then give you a Rytec Level password to enter into P.999
6. We will then change P.103 to a 460 from 230
7. Exit parameters and set the door limits
8. Operate door 5 times to get done with the calibration runs and make sure that door is operating correctly

Note: Depending on the version of software on your EPROM chip, you may be able to change P.103 without a Rytec Level Password.

If there are any questions, please call Rytec Customer Support at (800) 628-1909.